



Dimmer Compatibility Guide

Product Family Name:			
Item Number:	776611	776668	776669
Ordering Code:	LED7G25/27K/FIL/M/3	LED7A19/30K/FIL/2	LED7ST18/30K/FIL/2

	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes	
Incandescent/Halogens (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IP06	Good	1	6	Minor flicker at LE at 10% with 1, dims down to 0.1%	
		SureSlide	6633-P	Good	1	6	Minor flicker at LE at 10% with 1, dims down to 0.1%	
		Vivia	VPI06-1LZ	Good	1	6	Minor flicker at LE with 1, dims down to 0.1%	
		ToggleR	TG-600	Good	1	6	Minor flicker at LE at 10% with 1, dims down to 0.1%	
		Diva	DV-600	Good	1	6	Minor flicker at LE at 10% with 1, dims down to 0.1%	
	Lutron	SkyLark	S-600	Good	1	6	Minor flicker at LE at 10% with 1, dims down to 0.1%	
		Maestro	MAW-600	Good	4	6	Minor flicker at LE with 4-6, dims down to 0.1%	
		Titan	CD703-PW	Good	1	6	Minor flicker at LE with 1-3 dims down to 0.1%	
		Harmony	D703-PTC	Good	1	6	Minor flicker at LE with 1-2, dims down to 0.1%	
		Harmony	H703-PTC	Good	1	6	Minor flicker at LE with 1-2, dims down to 0.1%	
CFL/LED	Leviton	IllumaTech	IP06	Best	1	6	Dims down to 0.1% with 1-6	
		SureSlide	6674	Best	1	6	Dims down to 0.3% with 1-6	
		Decora	6672	Best	1	6	Dims down to 0.1% with 1-6	
		SkyLark Countour	CTL-153	Best	1	6	Dims down to 0.1% with 1-6	
		Diva	DVCL-153PL	Best	1	6	Dims down to 0.1% with 1-6	
	Lutron	Maestro	MAEL-153MLH	Best	1	6	Dims down to 0.1% with 1-6	
		SkyLark	SCL-153P	Best	1	6	Dims down to 0.1% with 1-6	
		ToggleR	TGCL-153PH	Best	1	6	Dims down to 0.1% with 1-6	
		Radio RA	RA2RR-6CL_PD	Best	1	6	Dims down to 0.1% with 1-6	
		Harmony	DCL453-PTC	Best	1	6	Dims down to 0.1% with 1-6	
Legrand	Harmony	HCL453PTC	Best	1	6	Dims down to 0.1% with 1-6		
	Adorne Paddle	ADPD453LM2	Best	1	6	Dims down to 0.1% with 1-6		
Electronic Low Voltage	Leviton	Vivia	VPE04	Good	1	6	Minor flicker at LE with 1-6, dims down to 0.1%	
		IllumaTech	IP604	Good	1	6	Minor flicker at LE with 1-6, dims down to 0.1%	
		Decora	6615-P	Good	1	6	Minor flicker at LE with 1-6, dims down to 0.1%	
		SkyLark Countour	CTELV-303P	Good	1	6	Minor flicker at Med with 1-6, dims down to 0.1%	
		Diva	DVELV-300P	Good	1	6	Minor flicker at Med with 1-4, dims down to 0.1%	
	Lutron	Maestro	MAELV-600	Good	1	6	Minor flicker at Med with 1-4, dims down to 0.1%	
		SkyLark	SLELV-300P	Good	1	6	Minor flicker at Med with 1-4, dims down to 0.1%	
		VIBRI	VTELV-600M-W	Good	1	6	Minor flicker at LE with 1-6, dims down to 0.1%	
		Scene Director	SCELV	Good	1	6	Minor flicker at LE with 1-6, dims down to 1%	
		Magnetic Low Voltage	Leviton	Vivia	VPM-06	Good	1	6
Decora	6613-P			Good	1	6	Minor flicker from 10-50% with 1, dims down to 0.1%	
Maestro	MALV-600			Bad	5	6	Dims down 1% with 5-6	
Lutron	Harmony		DL703-PW	Good	1	6	Flicker LE - Med with 1, dims down to 0.1%	
	Legrand		Titan	CDLV703-PW	Good	1	6	Flicker LE with 1, dims down to 0.1%
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX3-1BL2	Best	1	6	Dims down to 2%	
		Decora Smart Wi-Fi	DAXMG-18Z	N/A				
		Satellite Remote Control dimmer	N/A					
		Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Bad	1	6	Flashing at LE with 1, minor flicker at LE with 2-6
		Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1	N/A			
		Legrand	Adorne Sol Tap Wi-Fi TRU Universal	ADTP700RMTUW1	N/A			
		GE	Z WAVE	ZW3005	Best	1	6	Dims down to 7%
Universal	Legrand	Adorne SoftTap	ADTP703TU	Best	1	6	Dims down to 0.1%	
		Miro Decorator	DRD4-W	bad	1	6	Turn on with flash with 1-3, dims down to 0.1% with 4-6	
		Harmony	H703P/UTC	Best	1	6	Dims down to 0.1%	
		Adorne Whisper	ADWR700MMTUW2	Best	1	6	Dims down to 0.1%	
		Adorne Touch	ADTH700RMTUW2	Best	1	6	Dims down to 0.1%	
		Decorator	DAL6P-CX-K-L	Good	1	6	Minor flicker at LE with 1-6, dims down to 0.1%	
		Cooper	SAL6P-W-L	Good	1	6	Minor flicker at LE with 1-6, dims down to 0.1%	

¹ May experience "pop-on," lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	
Low End (L.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.

CONTACT INFORMATION:
Bulbrite Industries Inc.
145 West Commercial Avenue
Moonachie, New Jersey 07074
PHONE: 1-800-528-5555
FAX: 1-800-441-7708
Email: ProductSupport@bulbrite.com
©2017 Bulbrite Industries Inc.
All Rights Reserved.