



Dimmer Compatibility Guide

PLEASE NOTE: Compatibility list is based upon testing conducted by the manufacturer in a lab simulated environment. Actual results may vary.

Product Family Name: 770632
Item Number: LED5E12/30K/120/D
Ordering Code:

Lamps per Dimmer							
	Manufacturer	Product	Model Number	Overall Rating	Recommended Minimum	Maximum Tested*	Notes
Incandescent/Halogen (Triac/Phase Cut/Leading Edge Dimmers)	Leviton	IllumaTech	IPI06	Good	1	6	Dims down to 0.1%, minor flicker at 10% with 1
		SureSlide	6633-P	Good	1	6	
		Vizia	VP106-1LZ	Good	1	6	
		Toggle	TG-600	Good	1	6	Dims down to 0.1%, minor flicker at 100% & 30% with 1
	Lutron	Diva	DV-600	Good	1	6	Dims down to 0.1%, minor flicker at 10% with 1
		SkyLark	S-600	Good	1	6	Dims down to 0.1%, minor flicker at 10% with 1
		Maestro	MAIV-600	Bad	6	6	Dims down to 0.1% with 6
		Titan	CD703-PW	Bad	1	6	Flicker at 5% with 1, flicker at Med & LE with 2, flicker at LE with 3
	Legrand	Harmony	D703-PTC	Bad	1	6	Flicker at 5% with 1, flicker at 20% -30% with 2, flicker at 30% -40% with 3, flicker at 60% with 4, flicker at 30% with 5
		Harmony	H703-PTC	Bad	1	6	Flicker at 30% with 1, flicker at 100% with 2, flicker at 10 with 4, flicker at 30-80 with 5
CFL/LED	Leviton	IllumaTech	IPL06	Best	1	6	
		Sureslide	6674	Best	1	6	Dims down to 0.1% with 1-6
		Decora	6672	Best	1	6	Dims down to 0.1% with 1-6
		SkyLark Countour	CTCL-153	Good	1	6	Dims down to 0.1% with 1-6, minor flicker Med with 1
	Lutron	Diva	DVCL-153PL	Best	1	6	Dims down to 0.1% with 1-6
		Maestro	MACL-153MLH	Best	1	6	Dims down to 0.1% with 1-6
		SkyLark	SCL-153P	Best	1	6	Dims down to 0.1% with 1-6
		Toggle	TGCL-153PH	Best	1	6	Dims down to 0.1% with 1-6
		Radio RA	RA2RR-6CL-PD	Best	1	6	Dims down to 0.1% with 1-6
		Harmony	DCL453-PTC	Best	1	6	Dims down to 0.1% with 1-6
	Legrand	Harmony	HCL453PTC	Best	1	6	Dims down to 0.1% with 1-6
		Adorne Paddle	ADPD453LM2	Good	1	6	Dims down to 10% with 1-6, minor flicker at 50% & 90% with 1
Electronic Low Voltage	Leviton	Vizia	VPED4	Best	1	6	Dims down to 0.1% with 1-6
		IllumaTech	IPE04	Best	1	6	Dims down to 0.1% with 1-6
		Decora	6615-P	Good	1	6	Dims down to 20% with 1-6
		SkyLark Countour	CTELV-303P	Best	1	6	Dims down to 0.1% with 1-6
	Lutron	Diva	DVELV-300P	Best	1	6	Dims down to 0.1% with 1-6
		Maestro	MAELV-600	Best	1	6	Dims down to 0.1% with 1-6
		SkyLark	SCLV8-300P	Best	1	6	Dims down to 0.1% with 1-6
		VIERTI	VTEL-600M-W	Best	1	6	Dims down to 0.1% with 1-6
	Legrand	Scene Director	SCELV	Best	1	6	Dims down to 10% with 1-6
Magnetic Low Voltage	Leviton	Vizia	VPM-06	Good	2	6	Dims down to 0.1% with 1-6, Flicker at 20% with 4
		Decora	6613-P	Good	1	6	Dims down to 0.1% with 1-6, flicker at 60% -90% with 2
	Lutron	Maestro	MALV-600	Bad	6	6	Dims down to 0.1% with 6
		Harmony	DLV703-PW	Bad	1	6	Dims down to 0.1% with 1-6, flicker at 20% -30% with 1, flicker at 10% with 2, flicker at 30-50% with 3
	Legrand	Titan	CDLV703-PW	Bad	1	6	Dims down to 0.1% with 1-6, flicker at 100% with 1, flicker at 10% with 3, flicker at 20% with 4
Smart Dimmer	Leviton	Decora Digital (Bluetooth)	DDMX1-BLZ	Best	1	6	Dims down to 0.1% with 1-6
	Leviton	Decora Smart Wi-Fi	DX6HD-18Z	N/A			
	Insteon	SwitchLin Remote Control dimmer		N/A			
	Lutron	Caseta Wireless smart dimmer Wi-Fi	PD-6WCL	Good	1	6	Dims down to 0.1% with 1-6, Minor flicker at 4% with 1-6
	Legrand	Adorne touch Wi-Fi TRU Universal	ADTH700RMTUW1	N/A			
	Legrand	Adorne Sof Tap Wi-Fi TRU Universal	ADTP700RMTUW1	N/A			
	GE	Z WAVE	ZW300S	Best	1	6	Dims down to 0.1% with 1-6,
Universal	Legrand	Adorne Softap	ADTP703TU	Best	1	6	Dims down to 4% with 1-6
		Miro Decorator	DRD4-W	Best	1	6	Dims down to 0.1% with 1-6
		Harmony	H703PTUTC	Best	1	6	Dims down to 5% with 1-6
		Adorne Whisper	ADWR700MMMTUW2	Best	1	6	Dims down to 0.1% with 1-6
		Adorne Touch	ADTH700MMMTUW2	Best	1	6	Dims down to 0.1% with 1-6
		Decorator	DALD6P-C2-K-L	Good	1	6	Dims down to 0.1% with 1-6, flicker at 20% with 1
	Cooper	Decorator	DALD6P-C2-K-L	Good	1	6	Dims down to 0.1% with 1-6, flicker at 20% with 1
		Skye	SALD6P-W-K-L	Good	1	6	Dims down to 0.1% with 1-6, flicker at 20% with 1

*Maximum Tested (Lamps per Dimmer) - Additional lamps may work with your dimmer system. For maximum capacity please consult dimmer manufacturer.
†May experience "pop-on", lights cannot be turned on immediately to their minimum level. The slider needs to be raised above the minimum light level for the lights to first turn on if they were initially off. Then, the slider can be lowered to get to a lower light level; the dimmer cannot be turned on to just the minimum level.

Overall Rating	
Not Compatible	One or more of the following observed: Major flickering at various points, significant audible noise, no dimming range, does not turn off.
Bad	One or more of the following observed: Some flickering observed at various points, audible noise may be present, dimming not smooth.
Good	
	One or more of the following observed: Minor flickering at some point may exist. Dead travel may exist, which means there may be periods of time when the slider (or other form of control button) is moved without affecting the light level. These periods of dead travel are minor and most of the time not visible. Minor audible noise.
Best	Most of the following observed: No flickering, minimal audible noise (typically less than 25 dBA), wide dimming range - can dim down to 20% or less of light output.
High End (H.E.) Dead Travel	
Low End (L.E.) Dead Travel	Determines how much, if any, dead travel exists at the top and bottom of the dimmer's range. Dead travel is when the slider can be moved without affecting the light level.